

DEPENDENT RESURVEY OF THE THIRD STANDARD PARALLEL NORTH  
THROUGH A PORTION OF RANGE 19 EAST, MDM, NEVADA

CHAINS	
	S C T16N R19E S 31   S 32 <hr style="width: 50%; margin: auto;"/> 1989
	<p>from which</p> <p style="padding-left: 40px;">A fir, 16 ins. diam., bears N. 69°30' E., 410 lks. dist., mkd. T16N R19E SC S32 BT.</p> <p>A pine, 24 ins. diam., bears N. 56°45' W., 96<sup>1</sup>/<sub>2</sub> lks. dist., mkd. T16N R19E SC S31 BT.</p> <p>Cor. is located on moderate steep NE. slope on W. edge of willow patch in open drain area. Large fir and pine timber - 2 chs. S. and 3 chs. E. of cor. Stream, 8 lks. wide, course NW., bears E., 4.10 chs. dist.</p> <hr/> <p>S. 89°52'10" W., on the S. bdy. of sec. 31.</p>
1.90	Stream, 10 lks. wide, course N. 33° E.
34.254	Point for the <sup>1</sup> / <sub>4</sub> sec. cor. of sec. 6 only, T. 15 N., R. 19 E., hereinafter described in the field notes of the dependent resurvey of the subdivisional lines of T. 15 N., R. 19 E.
35.00	Ravine, drains N. 23° E.
39.820	<p>The stan. <sup>1</sup>/<sub>4</sub> sec. cor. of sec. 31, determined at the remains of the original post, found decay remains, 4 ins. diam., in depression 5 ins. deep, from which the remains of the original bearing trees</p> <p style="padding-left: 40px;">A pine stump, dead, down, and decaying, 28 ins. diam., bears S. 40°30' E., 11 lks. dist., with the scribe marks BT and chaining notch recovered in remains. (Record, S. 34° E., 12 lks.)</p> <p style="padding-left: 40px;">A fir stump hole, 24 ins. diam. bark ring, bears N. 62°00' W., 16 lks. dist. (Record, 11 lks.)</p> <p>At the corner point</p> <p>Set a stainless steel post, 28 ins. long, 2<sup>1</sup>/<sub>2</sub> ins. diam., 24 ins. in the ground with a magnet at base, and in a mound of stone, 5 ft. base, to top, with brass cap mkd.</p>
	SC T16N R19E <sup>1</sup> / <sub>4</sub> S 31 <hr style="width: 50%; margin: auto;"/> 1989
	<p>from which</p> <p style="padding-left: 40px;">A red fir, 19 ins. diam., bears N. 5°30' E., 125<sup>1</sup>/<sub>2</sub> lks. dist., mkd. <sup>1</sup>/<sub>4</sub> S31 SC BT.</p>